



Main

| | |
|------------------------|------------------------------|
| Product | Energy Efficient Transformer |
| Enclosure Code | 24D |
| Enclosure Type | NEMA 2 |
| Insulation Temperature | 428 °F (220 °C) |
| Phase | 1 phase |
| Primary Voltage | 240 x 480 V |
| Power Rating | 167 kVA |
| Secondary Voltage | 120/240 V |
| Full Capacity Taps | 6 2.5 % 2+ 4- |
| Temperature Rise | 150 °C |
| Winding Material | Aluminium |

Ordering and shipping details

| | |
|-----------------------|-------------------------------|
| Category | 16284 - 1 PH EE/TP1 LVGP XFMR |
| Discount Schedule | PE2E |
| GTIN | 00785901864547 |
| Nbr. of units in pkg. | 1 |
| Package weight(Lbs) | 1 lb(US) (0.45 kg) |
| Returnability | Yes |
| Country of origin | MX |

Packing Units

| | |
|------------------|-------------------|
| Package 1 Height | 4.44 ft (1.354 m) |
| Package 1 width | 2.46 ft (0.749 m) |
| Package 1 Length | 2.98 ft (0.909 m) |

Offer Sustainability

| | |
|----------------------------|---|
| Sustainable offer status | Green Premium product |
| California proposition 65 | WARNING: This product can expose you to chemicals including: Phenyl Glycidyl Ether, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov |
| REACH free of SVHC | Yes |
| EU RoHS Directive | Compliant EU RoHS Declaration |
| Toxic heavy metal free | Yes |
| Mercury free | Yes |
| RoHS exemption information | Yes |
| China RoHS Regulation | China RoHS Declaration |
| Environmental Disclosure | Product Environmental Profile |

Contractual warranty

| | |
|----------|-----------|
| Warranty | 18 months |
|----------|-----------|

The information provided in this documentation contains general descriptions and/or technical characteristics of the products of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.