

INVERTER GENERATOR





POWERING YOUR life.

> Model 201122


UPC **817198025742**

∑★ Warranty 3 Years











EZ START DIAL Confusion free ENGINE START-UP



ULTRA OUIET

LOW NOISE - high performance




ULTRALIGHT

Compact design weighs LESS THAN 40 LB.



PARALLEL READY

Link 2 units for DOUBLE POWER







20 AMP 120V, 5-20R



Parallel



Q Specifications

START TYPE

EMISSIONS

VOLTAGE (V) AC	120
DC VOLTS	5.0
ENGINE SIZE (cc)	79
FUEL TYPE	Gasoline or Propane
GASOLINE CAPACITY (gal.)	1.1
OIL TYPE	10W-30
OIL CAPACITY (fl. oz./mL)	16.9/500
LOW OIL SHUT-OFF	Yes

Recoil



CARBON MONOXIDE **AUTO-SHUTOFF SYSTEM**









Our 2500-watt inverter is one of the lightest in the industry, meets ANSI/PGMA G300-2018 requirements, and features CO Shield, the carbon monoxide auto shutoff system. Featuring Dual Fuel, allowing the 79cc engine to run on gasoline or propane, it provides up to 11.5 hours on gasoline or up to 34 hours with a 20-lb propane.

Inside the box

OIL FUNNEL

ENGINE OIL

GENERATOR PROPANE HOSE 2.3 FT. OPERATOR'S MANUAL

What You Need

GASOLINE OR PROPANE

EPA III/CARB (!) *Specifications, descriptions and illustrations are subject to change without notice.

