

NMV₁

Micron Vacuum Gauge

It uses the Pirani high-precision vacuum sensor to precisely measure vacuum levels. Digital display affords a comprehensive view of vacuum conditions. When reaching the preset vacuum level, it will buzz as a reminder. When the vacuum level increases from the preset vacuum level, it will buzz rapidly and flash the backlight to warn of leaks.

Empowering You to Work Smarter



Precise Measurement

Pirani Vacuum Sensor

- Professional grade
- More precise

Ergonomic Design

• Easy to carry

Large Backlit Display

- Easy-to-read large digital display
- Backlit for clarity
- Auto power off

Buzzing Alert

- Vacuum level reminder
- · Vacuum leakage warning

| Model | NMV1 |
|---------------------------|---|
| Maximum overload pressure | 14 psi |
| Range | 0~10000 Pa, 0~100 mBar, 0~75 mmHg, 0~75000 microns |
| Resolution | 0.01 (10 Pa), 0.0001 (10 mBar), 0.0001 (10 mmHg), 1 (30000 microns) |
| Accuracy | 15-750 micron: ±5% of reading (at 68°F) |
| Operating temperature | 32~122°F(0~50°C) |
| Unit | Pa, mBar, mmHg, microns |
| Sensor | Pirani sensor |
| Buzzer alarm | 90 dB, shut down after 10 seconds |
| Weight | 4.5 oz |
| Accessory | Storage Bag |
| | |

1-YEAR WARRANTY