

TRANSISTOR SOCKETS



✓ Active

TE CONNECTIVITY (TE)

8080-1G31=TRANSISTOR SOCKET AS

Augat | AD

8080-1G31

TE Internal Number: 4-1437504-3

Not EU RoHS Compliant Not EU ELV Compliant

Number of Positions 3

Package TO-3

Lead Size Accepted 1.52 mm [.06 in]

Termination Method Solder

Operating Temperature Range (°C) -55 – 125



PRODUCT DRAWING



→ 3D PDF



Product Drawings

TRANSISTOR SOCKET

PDF

English

CAD Files

3D PDF

PDF

3D

Customer View Model

2D_DXF.ZIP

English

3D_IGS.ZIP English	
Customer View Model 3D_STP.ZIP English	
FEATURES	+
Please review product documents or contact us for the latest agency approval information.	
Please Note: Use the Product Drawing for all design activity.	
Product Type Features	
Terminal Configuration Contact	
Package TO-3	
Product Type Socket	
Configuration Features	
Number of Positions 3	
Number of Solder Lugs 2	
Body Features	
Lead Size Accepted 1.52 mm [.06 in]	
Color Green or Blue	
Insulator Material Diallyl Phthalate (DAP)	
Contact Features	
Terminal Plating Tin-Lead	
Termination Method Solder Pin Diameter (in) .06	
Terminal Material Beryllium Copper	
Socket Type Transistor	
Usage Conditions	
Operating Temperature Range (°C) -55 – 125	
In division Chan dands	
Industry Standards Inculator Flammability Pating III 94V 0	
Insulator Flammability Rating UL 94V-0	
PRODUCT COMPLIANCE	+
Statement of Compliance	
Statement of Compliance	
PDF	

Customer View Model